




# IQ8H-240 Microinverter

Our newest IQ8 Microinverters are the industry's first microgrid-forming, software-defined microinverters with split-phase power conversion capability to convert DC power to AC power efficiently. The brain of the semiconductor-based microinverter is our proprietary application-specific integrated circuit (ASIC), which enables the microinverter to operate in grid-tied or off-grid modes. This chip is built in advanced 55 nm technology with high-speed digital logic and has superfast response times to changing loads and grid events, alleviating constraints on battery sizing for home energy systems.



Part of the Enphase Energy System, IQ8 Series Microinverters integrate with the IQ Battery, IQ Gateway, and the Enphase App monitoring and analysis software.



Connect PV modules quickly and easily to the IQ8 Series Microinverters that have integrated MC4 connectors.



IQ8 Series Microinverters redefine reliability standards with more than one million cumulative hours of power-on testing, enabling an industry-leading limited warranty of up to 25 years.



IQ8 Series Microinverters are UL listed as PV Rapid Shutdown Equipment and conform with various regulations when installed according to the manufacturer's instructions.

\*Meets UL 1741 only when installed with IQ System Controller 2 or 3.  
 \*\*IQ8H-240 support split-phase, 240 V.

## Easy to install

- Lightweight and compact with plug-and-play connectors
- Power line communication (PLC) between components
- Faster installation with simple two-wire cabling

## High productivity and reliability

- Produces power even when the grid is down\*
- More than one million cumulative hours of testing
- Class II double-insulated enclosure
- Optimized for the latest high-powered PV modules

## Microgrid-forming

- Complies with the latest advanced grid support\*\*
- Remote automatic updates for the latest grid requirements
- Configurable to support a wide range of grid profiles
- Meets CA Rule 21 (UL 1741-SA) and IEEE 1547:2018 (UL 1741-SB)

## NOTE:

- You cannot mix IQ8 Microinverters with previous generations of Enphase microinverters (IQ7 Series, IQ6 Series, and so on) in the same system.
- IQ Microinverters ship with default settings that meet North America's IEEE 1547 interconnection standard requirements. Region-specific adjustments may be requested by an Authority Having Jurisdiction (AHJ) or utility representative according to the IEEE 1547 interconnection standard. An IQ Gateway is required to make these changes during installation.

# IQ8H-240 Microinverter

INPUT DATA (DC)		UNITS	IQ8H-240-72-M-US
Commonly used module pairings <sup>1</sup>	W		320–540
Module compatibility	—	To meet compatibility, PV modules must be within the following maximum input DC voltage and maximum module $I_{sc}$ . Module compatibility can be checked at <a href="https://enphase.com/installers/microinverters/calculator">https://enphase.com/installers/microinverters/calculator</a> .	
MPPT voltage range	V		36–45
Operating range	V		16–58
Minimum/Maximum start voltage	V		22/58
Maximum input DC voltage	V		60
Maximum continuous input DC current	A		12
Maximum input DC short-circuit current	A		25
Maximum module ( $I_{sc}$ )	A		20
Overvoltage class DC port	—		II
DC port backfeed current	mA		0
PV array configuration	—	Ungrounded array; no additional DC side protection required; AC side protection requires max. 20 A per branch circuit	
OUTPUT DATA (AC)		UNITS	
Peak output power	VA		384
Maximum continuous output power	VA		380
Nominal voltage (L-L)	V		240, split-phase (L-L), 180°
Minimum and maximum grid voltage <sup>2</sup>	V		211–264
Maximum continuous output current	A		1.58
Nominal frequency	Hz		60
Extended frequency range	Hz		47–68
AC short-circuit fault current over three cycles	Arms		2
Maximum units per 20 A (L-L) branch circuit <sup>3</sup>	—		10
Total harmonic distortion	—		<5%
Overvoltage class AC port	—		III
AC port backfeed current	mA		30
Power factor setting	—		1.0
Grid-tied power factor (adjustable)	—		0.85 leading ... 0.85 lagging
Peak efficiency	%		97.6
CEC weighted efficiency	%		97
Nighttime power consumption	mW		22

(1) No enforced DC/AC ratio.

(2) The nominal voltage range can be extended beyond nominal if required by the utility.

(3) Limits may vary. Refer to local requirements to define the number of microinverters per branch in your area.

**MECHANICAL DATA**

Dimensions (H × W × D)	mm	212 mm (8.3") × 175 mm (6.9") × 30.2 mm (1.2")
Weight	kg	1.1 kg (2.43 lbs)
Ambient temperature range	°C	-40°C to 60°C (-40°F to 140°F)
Relative humidity range	%	4% to 100% (condensing)
DC connector type	—	Stäubli MC4
Altitude	m	<2,600 m (8,530 ft)
Cooling	—	Natural convection – no fans
Approved for wet locations	—	Yes
Pollution degree	—	PD3
Enclosure	—	Class II double-insulated, corrosion-resistant polymeric enclosure
Environmental category/UV exposure rating	—	NEMA Type 6/outdoor

**COMPLIANCE**

Certifications	CA Rule 21 (UL 1741-SA), UL 62109-1, IEEE 1547:2018 (UL 1741-SB), FCC Part 15 Class B, ICES-0003 Class B, CAN/CSA-C22.2 NO. 107.1-01. This product is UL Listed as PV Rapid Shutdown Equipment and conforms with NEC 2014, NEC 2017, NEC 2020, and NEC 2023 section 690.12 and C22.1-2018 Rule 64-218 Rapid Shutdown of PV Systems for AC and DC conductors when installed according to the manufacturer's instructions.
----------------	---

# Revision history

REVISION	DATE	DESCRIPTION
DSH-00245-2.0	February 2024	Updated the information about IEEE 1547 interconnection standard requirements.
DSH-00245-1.0	November 2023	Updated module compatibility specification and NEC 2023 specification in the “Compliance” section.
Previous releases.		